



NVIDIA Data Center GPU Driver version 550.127.05 (Linux)/ 553.24 (Windows)

Release Notes

Table of Contents

Chapter 1. Version Highlights.....	1
1.1. Software Versions.....	1
1.2. Fixed Issues.....	1
1.3. Known Issues.....	2
Chapter 2. Virtualization.....	3
Chapter 3. Hardware and Software Support.....	5

Chapter 1. Version Highlights

This section provides highlights of the NVIDIA Data Center GPU R550 Driver (version 550.127.05 Linux and 553.24 Windows).

For changes related to the 550 release of the NVIDIA display driver, review the file "NVIDIA_Changelog" available in the .run installer packages.

- ▶ Linux driver release date: 10/22/2024
- ▶ Windows driver release date: 10/22/2024

1.1. Software Versions

For this release, the software versions are as follows:

- ▶ CUDA Toolkit 12: 12.4
Note that starting with CUDA 11, individual components of the toolkit are versioned independently. For a full list of the individual versioned components (for example, nvcc, CUDA libraries, and so on), see the [CUDA Toolkit Release Notes](#).
- ▶ NVIDIA Data Center GPU Driver: 550.127.05 (Linux) / 553.24 (Windows)
- ▶ Fabric Manager: 550.127.05 (Use `nv-fabricmanager -v`)
- ▶ NVFlash: 5.791

For more information on getting started with the NVIDIA Fabric Manager on NVSwitch-based systems (for example, NVIDIA HGX A100), refer to the [Fabric Manager User Guide](#).

1.2. Fixed Issues

- ▶ Fixed an issue in the kernel driver Xid reporting callback mechanism that caused string corruption in the reported error message. The affected error reporting callback registration symbols have also been renamed to help users of the API identify drivers that have the fix. [4766627]
- ▶ The UVM driver no longer relies on always getting response from the HW and now checks GPU health state whenever expecting a response. [4732563]
- ▶ Fixed a race condition in driver event notification, resulting in event use after free, and causing a kernel panic. [4685412]

- ▶ Resolved interrupt storm related to ECC limit counters. [4607641]
- ▶ Fixed RC error during channel construct by skipping channel preemption when channel is not already scheduled. [4599733]
- ▶ Due to a bug in `nvidia-smi` code related to handling of multiple devices, the `nvidia-smi topo -m` display was corrupted. This has been fixed in the latest drivers. [4593303]
- ▶ The NVIDIA driver now better identifies large page system memory allocations when using Window TCC mode. This should provide performance improvements for `cudaHostRegister` calls when registering user-provided large page system memory allocations. [4553500]
- ▶ Fixed a segmentation fault when using `cudaMalloc` in CUDA driver that was affecting certain applications. [4511621]
- ▶ Added more error checking when doing remote procedure calls from the host kernel driver to the GPU System Processor (GSP). This avoids emitting misleading or redundant kernel logs and waiting for extra timeouts in error paths where it is already known that communicating with the GSP will fail, for example if the GPU has fallen off the system bus. [4265317]
- ▶ Fixed an issue in Fabric Manager that incorrectly detected the underlying system, resulting in the loading of an incorrect FM NVLink topology file. This issue caused GPU NVLink P2P traffic to fail with Xid/SXid errors. [4701808]
- ▶ Refer to the [nvidia-smi](#) man page's change log for the latest updates. [4783082]

1.3. Known Issues

None.

Chapter 2. Virtualization

To make use of GPU passthrough with virtual machines running Windows and Linux, the hardware platform must support the following features:

- ▶ A CPU with hardware-assisted instruction set virtualization: Intel VT-x or AMD-V.
- ▶ Platform support for I/O DMA remapping.
- ▶ On Intel platforms, the DMA remapper technology is called Intel VT-d.
- ▶ On AMD platforms, it is called AMD IOMMU.

Support for these features varies by processor family, product, and system, and should be verified at the manufacturer's website.

The following hypervisors are supported for virtualization:

Hypervisor	Notes
Citrix XenServer	Version 6.0 and later
VMware vSphere (ESX / ESXi)	Version 5.1 and later.
Red Hat KVM	Red Hat Enterprise Linux 7 with KVM
Microsoft Hyper-V	Windows Server 2019 Hyper-V Generation 2

Data Center products now support one display of up to 2560x1600 resolution.

The following GPUs are supported for device passthrough for virtualization:

GPU Family	Boards Supported
NVIDIA Ada Lovelace	NVIDIA L40, L4
NVIDIA Grace Hopper	NVIDIA GH200
NVIDIA Hopper	NVIDIA H100, NVIDIA H800
NVIDIA Ampere GPU Architecture	NVIDIA A800, A100, A40, A30, A16, A10, A10G, A2, AX800
NVIDIA Turing	NVIDIA T4, NVIDIA T4G
NVIDIA Volta	NVIDIA V100
NVIDIA Pascal	Quadro: P2000, P4000, P5000, P6000, GP100

GPU Family	Boards Supported
NVIDIA Maxwell	Tesla: P100, P40, P4
	Quadro: K2200, M2000, M4000, M5000, M6000, M6000 24GB
	Tesla: M60, M40, M6, M4

Chapter 3. Hardware and Software Support

Support for these features varies by processor family, product, and system, and should be verified at the manufacturer's website.

Supported Operating Systems for NVIDIA Data Center GPUs

The Release 550 driver is supported on the following operating systems:

- ▶ Windows x86_64 operating systems:
 - ▶ Microsoft Windows® Server 2022
 - ▶ Microsoft Windows® 11 21H2 - SV1
 - ▶ Microsoft Windows® 11 22H2 - SV2
 - ▶ Microsoft Windows® 11 23H2
 - ▶ Microsoft Windows® 10 21H2
 - ▶ Microsoft Windows® 10 22H2
- ▶ The following table summarizes the supported Linux 64-bit distributions. For a complete list of distributions, kernel versions supported, see the [CUDA Linux System Requirements](#) documentation.

Distribution	x86_64	Arm64 Server
Debian 12.x (where x <= 7)	Yes	No
Debian 11.x (where x <= 11)**	Yes	No
Debian 10. x (where x <= 13)**	Yes	No
OpenSUSE Leap 15.x (where y <= 6)	Yes	No
Fedora 39**	Yes	No
Red Hat Enterprise Linux 9.y (where y <= 4)	Yes	Yes
Rocky Linux 9.y (where y <= 4)	Yes	No

Distribution	x86_64	Arm64 Server
Red Hat Enterprise Linux 8.y (where y <= 10)	Yes	Yes
Rocky Linux 8.y (where y <= 10)	Yes	No
Red Hat Enterprise Linux / CentOS 7.y (where y <= 9)	Yes	No
SUSE Linux Enterprise Server 15.y (where y <= 6)	Yes	Yes
Ubuntu 24.04.z LTS (where z <= 1)	Yes	Yes
Ubuntu 22.04.z LTS (where z <= 5)	Yes	Yes
Ubuntu 20.04.z LTS (where z <= 6)	Yes	Yes
KylinOS V10 SP3	Yes	No
Azure Linux 2.0*	Yes	No

*Azure Linux will be supported by TRD via runfile. CUDA Toolkit will not support this OS as this is a deployment OS.

** Deprecated.

Supported Operating Systems and CPU Configurations for NVIDIA HGX H20

- ▶ Hopper Linux distributions:
 - ▶ Red Hat Enterprise Linux 9.4
 - ▶ Ubuntu 24.04 with NVIDIA HWE kernel
 - ▶ Ubuntu 22.04 with NVIDIA HWE kernel
- ▶ Windows 64-bit distributions:
 - ▶ Windows Server 2022

Supported Operating Systems and CPU Configurations for NVIDIA HGX GH200

- ▶ Grace Hopper Linux distributions:
 - ▶ Red Hat Enterprise Linux 9.4
 - ▶ SUSE Linux Enterprise Server 15 SP5 QU1
 - ▶ Ubuntu 24.04.1 with NVIDIA HWE kernel

- ▶ Ubuntu 22.04.2 with NVIDIA HWE kernel
- RHEL and SLES feature parity with NVIDIA HWE Kernels. The latest RHEL 9 and SLES 15 SP5 kernels support bare metal.

Supported Operating Systems and CPU Configurations for NVIDIA HGX H200

The Release 550 driver is validated with NVIDIA HGX H200 on the following operating systems and CPU configurations:

- ▶ Linux 64-bit distributions:
 - ▶ Red Hat Enterprise Linux 9.4 (in 4/8/16-GPU configurations)
 - ▶ Rocky Linux 9.4 (in 4/8/16-GPU configurations)
 - ▶ Ubuntu 24.04.1 LTS (in 4/8/16-GPU configurations)
 - ▶ Ubuntu 22.04.2 LTS (in 4/8/16-GPU configurations)
- ▶ Windows 64-bit distributions:
 - ▶ Windows Server 2022
 - ▶ Windows is supported only in shared NVSwitch virtualization configurations.

Supported Operating Systems and CPU Configurations for NVIDIA HGX H100/H800

The Release 550 driver is validated with NVIDIA HGX H100 on the following operating systems and CPU configurations:

- ▶ Linux 64-bit distributions:
 - ▶ Red Hat Enterprise Linux 8.10 (in 4/8/16-GPU configurations)
 - ▶ Red Hat Enterprise Linux 9.4 (in 4/8/16-GPU configurations)
 - ▶ Rocky Linux 9.4 (in 4/8/16-GPU configurations)
 - ▶ SUSE Linux Enterprise Server 15.6 (in 4/8/16-GPU configurations)
 - ▶ Ubuntu 24.04.1 LTS (in 4/8/16-GPU configurations)
 - ▶ Ubuntu 22.04.2 LTS (in 4/8/16-GPU configurations)
- ▶ Windows 64-bit distributions:
 - ▶ Windows Server 2022
 - ▶ Windows is supported only in shared NVSwitch virtualization configurations.

Supported Operating Systems and CPU Configurations for NVIDIA HGX A100/A800

The Release 550 driver is validated with NVIDIA HGX A100 on the following operating systems and CPU configurations:

- ▶ Linux 64-bit distributions:
 - ▶ Debian 12.7
 - ▶ Debian 11.10
 - ▶ Debian 10.13
 - ▶ Red Hat Enterprise Linux 8.10 (in 4/8/16-GPU configurations)
 - ▶ Red Hat Enterprise Linux 7.9 (in 4/8/16-GPU configurations)
 - ▶ Rocky Linux 8.10 (in 4/8/16-GPU configurations)
 - ▶ Red Hat Enterprise Linux 9.4 (in 4/8/16-GPU configurations)
 - ▶ CentOS Linux 7.9 (in 4/8/16-GPU configurations)
 - ▶ Ubuntu 24.04.1 LTS (in 4/8/16-GPU configurations)
 - ▶ Ubuntu 22.04.5 LTS (in 4/8/16-GPU configurations)
 - ▶ Ubuntu 20.04.6 LTS (in 4/8/16-GPU configurations)
 - ▶ SUSE SLES 15.6 (in 4/8/16-GPU configurations)
 - ▶ KylinOS V10 SP2
- ▶ Windows 64-bit distributions:
 - ▶ Windows Server 2022
 - ▶ Windows is supported only in shared NVSwitch virtualization configurations.
- ▶ CPU Configurations:
 - ▶ AMD Rome in PCIe Gen4 mode
 - ▶ Intel Skylake/Cascade Lake (4-socket) in PCIe Gen3 mode

Supported Virtualization Configurations

The Release 550 driver is validated with NVIDIA HGX A100, HGX A800, H100, and H800 on the following configurations:

- ▶ Passthrough (full visibility of GPUs and NVSwitches to guest VMs):
 - ▶ 8-GPU configurations with Ubuntu 20.04.6, 22.4.2, and 24.04.1
- ▶ Shared NVSwitch (guest VMs only have visibility of GPUs and full NVLink bandwidth between GPUs in the same guest VM):
 - ▶ 1/2/4/8/16-GPU configurations with Ubuntu 20.04.6 LTS

API Support

This release supports the following APIs:

- ▶ NVIDIA® CUDA® 12.4 for NVIDIA® Maxwell™, Pascal™, Volta™, Turing™, Hopper™, NVIDIA Ampere architecture, and NVIDIA Ada Lovelace GPU architecture GPUs
- ▶ OpenGL® 4.6
- ▶ Vulkan® 1.3
- ▶ DirectX 11
- ▶ DirectX 12 (Windows 10)
- ▶ Open Computing Language (OpenCL™ software) 3.0

Note that for using graphics APIs on Windows (such as OpenGL, Vulkan, DirectX 11, and DirectX 12) or any WDDM 2.0+ based functionality on Data Center GPUs, vGPU is required. See the [vGPU documentation](#) for more information.

Supported NVIDIA Data Center GPUs

The NVIDIA Data Center GPU driver package is designed for systems that have one or more Data Center GPU products installed. This release of the driver supports CUDA C/C++ applications and libraries that rely on the CUDA C Runtime and/or CUDA Driver API.

Attention: Release 470 was the last driver branch to support Data Center GPUs based on the NVIDIA Kepler architecture. This includes discontinued support for the following compute capabilities:

- ▶ sm_30 (NVIDIA Kepler)
- ▶ sm_32 (NVIDIA Kepler)
- ▶ sm_35 (NVIDIA Kepler)
- ▶ sm_37 (NVIDIA Kepler)

For more information on GPU products and compute capability, see <https://developer.nvidia.com/cuda-gpus>.

NVIDIA Server Platforms	
Product	Architecture
NVIDIA HGX H20 8-GPU	H20 and NVSwitch
NVIDIA HGX H100 8-GPU	H100 and NVSwitch
NVIDIA HGX H800 8-GPU	H800 and NVSwitch
NVIDIA HGX H100 4-GPU	H100 and NVLink
NVIDIA HGX A800 8-GPU	A800 and NVSwitch
NVIDIA HGX A100 8-GPU	A100 and NVSwitch
NVIDIA HGX A100 4-GPU	A100 and NVLink

NVIDIA Server Platforms	
Product	Architecture
NVIDIA HGX-2	V100 and NVSwitch

Data Center L-Series Products	
Product	GPU Architecture
NVIDIA L2	NVIDIA Ada Lovelace
NVIDIA L20	NVIDIA Ada Lovelace
NVIDIA L40	NVIDIA Ada Lovelace
NVIDIA L40S	NVIDIA Ada Lovelace
NVIDIA L4	NVIDIA Ada Lovelace

Data Center H-Series Products	
Product	GPU Architecture
NVIDIA H100 PCIe	NVIDIA Hopper
NVIDIA H100 NVL	NVIDIA Hopper
NVIDIA H800 PCIe	NVIDIA Hopper
NVIDIA H800 NVL	NVIDIA Hopper

RTX-Series / T-Series Products	
Product	GPU Architecture
NVIDIA RTX 6000 Ada Generation	NVIDIA Ada Lovelace
NVIDIA RTX 4000 SFF Ada Generation	NVIDIA Ada Lovelace
NVIDIA RTX A6000	NVIDIA Ampere architecture
NVIDIA RTX A5000	NVIDIA Ampere architecture
NVIDIA RTX A4000	NVIDIA Ampere architecture
Quadro RTX 8000	NVIDIA Turing
Quadro RTX 6000	NVIDIA Turing
Quadro RTX 4000	NVIDIA Turing
NVIDIA T1000	NVIDIA Turing
NVIDIA T600	NVIDIA Turing
NVIDIA T400	NVIDIA Turing

Data Center A-Series Products	
Product	GPU Architecture
NVIDIA A2	NVIDIA Ampere architecture
NVIDIA A800, AX800	NVIDIA Ampere architecture
NVIDIA A100X	NVIDIA Ampere architecture
NVIDIA A100	NVIDIA Ampere architecture
NVIDIA A100 80 GB PCIe	
NVIDIA A40	NVIDIA Ampere architecture
NVIDIA A30, A30X	NVIDIA Ampere architecture
NVIDIA A16	NVIDIA Ampere architecture
NVIDIA A10, A10M, A10G	NVIDIA Ampere architecture

Data Center T-Series Products	
Product	GPU Architecture
NVIDIA T4, T4G	NVIDIA Turing

Data Center V-Series Products	
Product	GPU Architecture
NVIDIA V100	Volta

Data Center P-Series Products	
Product	GPU Architecture
NVIDIA Tesla P100	NVIDIA Pascal
NVIDIA Tesla P40	NVIDIA Pascal
NVIDIA Tesla P4	NVIDIA Pascal

Data Center M-Class Products	
Product	GPU Architecture
NVIDIA Tesla M60	Maxwell
NVIDIA Tesla M40 24 GB	Maxwell
NVIDIA Tesla M40	Maxwell
NVIDIA Tesla M6	Maxwell
NVIDIA Tesla M4	Maxwell

Notice

This document is provided for information purposes only and shall not be regarded as a warranty of a certain functionality, condition, or quality of a product. NVIDIA Corporation ("NVIDIA") makes no representations or warranties, expressed or implied, as to the accuracy or completeness of the information contained in this document and assumes no responsibility for any errors contained herein. NVIDIA shall have no liability for the consequences or use of such information or for any infringement of patents or other rights of third parties that may result from its use. This document is not a commitment to develop, release, or deliver any Material (defined below), code, or functionality.

NVIDIA reserves the right to make corrections, modifications, enhancements, improvements, and any other changes to this document, at any time without notice.

Customer should obtain the latest relevant information before placing orders and should verify that such information is current and complete.

NVIDIA products are sold subject to the NVIDIA standard terms and conditions of sale supplied at the time of order acknowledgement, unless otherwise agreed in an individual sales agreement signed by authorized representatives of NVIDIA and customer ("Terms of Sale"). NVIDIA hereby expressly objects to applying any customer general terms and conditions with regards to the purchase of the NVIDIA product referenced in this document. No contractual obligations are formed either directly or indirectly by this document.

NVIDIA products are not designed, authorized, or warranted to be suitable for use in medical, military, aircraft, space, or life support equipment, nor in applications where failure or malfunction of the NVIDIA product can reasonably be expected to result in personal injury, death, or property or environmental damage. NVIDIA accepts no liability for inclusion and/or use of NVIDIA products in such equipment or applications and therefore such inclusion and/or use is at customer's own risk.

NVIDIA makes no representation or warranty that products based on this document will be suitable for any specified use. Testing of all parameters of each product is not necessarily performed by NVIDIA. It is customer's sole responsibility to evaluate and determine the applicability of any information contained in this document, ensure the product is suitable and fit for the application planned by customer, and perform the necessary testing for the application in order to avoid a default of the application or the product. Weaknesses in customer's product designs may affect the quality and reliability of the NVIDIA product and may result in additional or different conditions and/or requirements beyond those contained in this document. NVIDIA accepts no liability related to any default, damage, costs, or problem which may be based on or attributable to: (i) the use of the NVIDIA product in any manner that is contrary to this document or (ii) customer product designs.

No license, either expressed or implied, is granted under any NVIDIA patent right, copyright, or other NVIDIA intellectual property right under this document. Information published by NVIDIA regarding third-party products or services does not constitute a license from NVIDIA to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property rights of the third party, or a license from NVIDIA under the patents or other intellectual property rights of NVIDIA.

Reproduction of information in this document is permissible only if approved in advance by NVIDIA in writing, reproduced without alteration and in full compliance with all applicable export laws and regulations, and accompanied by all associated conditions, limitations, and notices.

THIS DOCUMENT AND ALL NVIDIA DESIGN SPECIFICATIONS, REFERENCE BOARDS, FILES, DRAWINGS, DIAGNOSTICS, LISTS, AND OTHER DOCUMENTS (TOGETHER AND SEPARATELY, "MATERIALS") ARE BEING PROVIDED "AS IS." NVIDIA MAKES NO WARRANTIES, EXPRESSED, IMPLIED, STATUTORY, OR OTHERWISE WITH RESPECT TO THE MATERIALS, AND EXPRESSLY DISCLAIMS ALL IMPLIED WARRANTIES OF NONINFRINGEMENT, MERCHANTABILITY, AND FITNESS FOR A PARTICULAR PURPOSE. TO THE EXTENT NOT PROHIBITED BY LAW, IN NO EVENT WILL NVIDIA BE LIABLE FOR ANY DAMAGES, INCLUDING WITHOUT LIMITATION ANY DIRECT, INDIRECT, SPECIAL, INCIDENTAL, PUNITIVE, OR CONSEQUENTIAL DAMAGES, HOWEVER CAUSED AND REGARDLESS OF THE THEORY OF LIABILITY, ARISING OUT OF ANY USE OF THIS DOCUMENT, EVEN IF NVIDIA HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES. Notwithstanding any damages that customer might incur for any reason whatsoever, NVIDIA's aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the Terms of Sale for the product.

Trademarks

NVIDIA and the NVIDIA logo are trademarks and/or registered trademarks of NVIDIA Corporation in the United States and other countries. Other company and product names may be trademarks of the respective companies with which they are associated.

Copyright

© 2024 NVIDIA Corporation & affiliates. All rights reserved.